

PRODUCT FACT SHEET

SIEGE® X USB / SIEGE® X

MULTI FUEL - LI-ION USB RECHARGEABLE BATTERY PACK or 2x CR123 - POWERED LANTERN

MARKET

APPLICATIONS: Outdoor, Sporting Goods, Automotive, Hardware/Do-It-Yourself, Industrial, Emergency Medical Services,

Safety, Gift, Consumer, Pest Control, Boating

DESCRIPTION: The Siege® X USB or Siege® X lantern features three lighting modes and multiple lighting levels. Multiple

white LEDs provide smooth lantern lighting, three red LEDs are used to preserve night vision and a white power LED for the flashlight mode. The lantern can use either a proprietary Streamlight SL-B26™ USB rechargeable cell pack or two CR123 disposable batteries and has a battery level indicator built into the on/off button. The D ring on the bottom makes it easy to hang the light for large area lighting needs. Battery replacement is a breeze, a quarter turn is all it takes to remove the bottom battery cover.

CASE MATERIAL: Tough Polycarbonate thermoplastic construction with elastomer over mold. Available in Coyote color.

DIMENSIONS: Base Diameter: 2.12 in. (5.38 cm) Height: 4.35 in (11.05 cm)
WEIGHT: 6.8 oz (192.78 grams) with CR123 batteries (Not included with purchase).

7.2 oz (204.12 grams) with P/N 220115 18650 battery (Included with purchase).

LENS: Unbreakable polycarbonate lenses.

LIGHT SOURCE: Lantern - Multiple white LEDs, three Red LEDs, and One (1) White power LED, impervious to shock with a

50,000 hour lifetime for the Flashlight mode.

LIGHT OUTPUT: Lantern Lumens Flashlight Lumens, Candela, Distance

High - 325 Lumens Red High - 1.6 Lumens High - 300 Lumens, 6000 Candela, 155m Medium - 170 Lumens Red SOS flashes at "Red high lumen level" Low - 40 Lumens, 900 Candela, 60m

Low - 30 Lumens

ON/OFF: White Output Modes = Low, Medium, High and Off

Red Output Modes = High, Flash SOS and Off Flashlight modes = Low, High and Off

To change the lanterns color from white to red, press and hold the on/off button for two seconds until the light changes color. Release the button. To then change to Flashlight mode, press and hold the on/off button for two seconds until the light changes to the flashlight beam. Release the button. To change back to Lantern mode, press and hold the button.

Switching Output Modes: Pushing the button within 1.5 seconds of the last button push will change the light level. You may sequence through all light levels and then to off.

NOTE: If you wait more than two seconds between button pushes, the next press of the button will turn the

light off.

RUN TIME: All claims to 10% of initial lumen output.

Lantern High = 4.5 Hrs Red = 22 Hrs Flashlight High = 3.5 Hrs Lantern Med. = 7.75 Hrs SOS = 90 Hrs Flashlight Low = 25 Hrs

Lantern Low = 25 Hrs

BATTERY: One Streamlight SL-B26™ Rechargeable cell pack or Two CR123 Lithium batteries.

FEATURES: LED technology for extreme brightness.

Battery Indicator in the on/off button- Changes from Green to Yellow to Red and then Flashing Red when

the batteries are at the end of their useable life.

IPX7 rated for water proof operation. (1 meter submersion)

2 meter impact resistance tested.

D-Ring on bottom for easy attachment. Spring loaded to fold out of the way when not in use. Ergonomic handle - Makes the light easy to carry and is designed to hook on any edge or bar.

WARRANTY: Streamlight's Limited Lifetime Warranty

APPROVALS: CE Meets applicable European Community directives.

(Siege® X USB only).

OPTIONAL

ACCESSORIES: None

Issued: 10/18/2018

Revised: 2/16/2021 **Rev:** 3 Made in China. **Document #326**